

Active - Cellular	Standard LTE with GNSS			LTE Advanced Pro with GNSS	5G-NR with GNSS	LTE 450	GSM-R
	EMEA	US (AT&T, Rogers)	APAC	NA, LATAM, EMEA, APAC	EMEA, NA, APAC	EMEA	EMEA
Modem Region	EMEA	US (AT&T, Rogers)	APAC	NA, LATAM, EMEA, APAC	EMEA, NA, APAC	EMEA	EMEA
Modem Vendor, Type	Teitit LE910C4-EU	u-blox TOBY-L200	u-blox TOBY-L280	Teitit LN920A12-WW	Teitit FN980	Cellient MPL200	Triorail TRM-5
Status / Effective	Available	Available	Available	Available	Available	Available	Available
5G NR	n.a.	n.a.	n.a.	n.a.	n1, n3, n5, n7, n8, n20, n25, n28, n38, n40, n41, n66, n71, n77, n78, n79	n.a.	n.a.
LTE Bands	B1, B3, B7, B8, B20, B28	B2, B4, B5, B7, B17	B1, B3, B5, B7, B8, B28	B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B38, B39, B40, B41, B42, B43, B48 (CBRS), B66, B71	B1, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29DL, B30, B32, B34, B38, B39, B40, B41, B42, B46(CRS), B66, B71	B3, B7, B20, B31	n.a.
DC-HSPA+/UMTS Bands (MHz)	B1(2100), B3(1800), B8(900)	B1(2100), B2(1900), B4(AWS), B5(850), B8(900)	B1(2100), B2(1900), B5(850), B8(900)	B1, B2, B4, B5, B6, B8, B9, B19	B1, B2, B3, B4, B5, B6, B8, B9, B19	B1(2100), B8(900)	n.a.
GSM/GPRS/EDGE Bands (MHz)	B3(1800), B8(900)	B2(1900), B3(1800), B5(850), B8(900)	B2(1900), B3(1800), B5(850), B8(900)	n.a.	n.a.	B8(900), B3(1800)	GSM-R, B8(900), B3(1800)
LTE Category	4	4	4	12	20	3	n.a. (GPRS class 10)
MIMO	2x2	2x2	2x2	2x2	4x4	2x2	n.a. (SISO)
Data Rates (max): downlink / uplink	150 Mbps / 50 Mbps	150 Mbps / 50 Mbps	150 Mbps / 50 Mbps	600 Mbps / 150 Mbps	5.5 Gbps / 2.7 Gbps	100 Mbps / 50 Mbps	85.6 kbps / 42.8 kbps
Voice, Audio	yes - CSFB, VoLTE	yes - CSFB	yes - CSFB	n.a.	n.a.	n.a.	yes
GNSS Support	GPS, Galileo, GLONASS, BeiDou	GPS, Galileo, GLONASS, BeiDou	GPS, Galileo, GLONASS, BeiDou	GPS, Galileo, GLONASS, BeiDou	GPS, Galileo, GLONASS, BeiDou	n.a.	n.a.
Tracking Sensitivity	up to -160 dBm	Up to -165 dBm	Up to -165 dBm	Up to -160 dBm	Up to -161 dBm	n.a.	n.a.
Assisted GPS	no	yes	yes	no	no	n.a.	n.a.
GNSS Chipset	Modem built-in	u-blox M8	u-blox M8	Modem built-in	Modem built-in	n.a.	n.a.
Form Factor	miniPCle	miniPCle / LGA	miniPCle / LGA	M2 (with miniPCle adapter)	M2 (with miniPCle adapter)	miniPCle	miniPCle
NetModule Product Codes	"-L", "-L-G"	"-Lbb", "-Lbb-G"	"-Lg", "-Lg-G"	"-Lp, -Lp-G"	"-N", "-N-G"	"-La"	"-Gr"
Technically Supported Routers	NB3800(Rev.≥C) NB3701(Rev.≥C) NB2800(Rev.≥C) NB28100(Rev.≥C) NB1800(Rev.≥C) NB1810(Rev.≥C)	NB800 (Rev.≥B), NG800, NB1601 (Rev.≥B), NB1800(Rev.≥B), NB1810(Rev.≥B), NB2700, NB2800, NB2810, NB3701, NB3800(Rev.≥B)	NB800 (Rev.≥B), NG800, NB1601(Rev.≥B), NB1800(Rev.≥B), NB1810(Rev.≥B), NB2700, NB2800, NB2810, NB3701, NB3800(Rev.≥B)	NB3800(Rev.≥C) NB2800(Rev.≥C) NB28100(Rev.≥C) NB1800(Rev.≥C) NB1810(Rev.≥C)	NB3800(Rev.≥C) NB2800(Rev.≥C) NB28100(Rev.≥C) NB1800(Rev.≥C) NB1810(Rev.≥C)	NB2700, NB2800, NB2810, NB3701, NB3800(Rev.≥B)	NB1601(Rev.≥B), NB3701, NB3800(Rev.≥B)
Required NetModule Router Software	4.7.0.100 and later	4.2.0.104 and later	3.8.0.114 and later	4.7.0.100 and later	4.7.0.100 and later	4.0.0.100 and later	4.0.0.100 and later

Active Cellular-Overview - 31.12.2022

Errors reserved